



Features:

Logistic

EUROLITE LED Pixel Tube 360° clear 0,5m

DMX LED tube for truss installation or ceilings

- Lightweight plastic tube
- 360° beam angle
- Equipped with 28 TCL LEDs, every tube is divided in 7 pixels with 4 LEDs each
- Functions: static colors, RGB color blend, internal programs, dimmer and strobe settings via DMX, Master/Slave
- Controllable via EUROLITE LED PSU-24V/4 DC controller; needed for operating the unit and not included in the delivery
- 4 LED Pixel Tubes 360° can be used with one controller
- Ideal for discotheques and clubs
- Control via Art-Net; stand-alone; DMX

EUROLITE LED PSU-24V/4 DC LED Tube 360°

Controller for EUROLITE LED Pixel Tubes 360°

- Controller and power supply unit for 4 LED light tubes
- Color change adjustable; Dimmer electronic; color blend stepless
- Strobe effect
- Can be operated in 5; 7; 14; 84; 192; 312 CH mode
- Control via stand-alone; DMX; sound to light via microphone; master/slave function

- 3 digit 7-segment LED display

Technical specifications:

EUROLITE LED Pixel Tube 360° clear 0,5m

Power consumption:	5.00 W
Control:	Art-Net; stand-alone; DMX
Beam angle (1/2 peak):	360°
Dimensions:	Length: 52.5 cm Depth: 5 cm Height: 5 cm
Weight:	0.30 kg
LED type:	SMD TCL 5050
LED number:	28
Beam angle:	360°
Dimensions (L x W x H):	525 x 50 x 50 mm

EUROLITE LED PSU-24V/4 DC LED Tube 360°

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	95.00 W
Power connection:	Mains input via IEC connector (M) mounting version power supply cord with safety plug (provided)
Power output:	1 x IEC connector (F) mounting version
DMX channels:	5; 7; 14; 84; 192; 312
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	Stand-alone; DMX; sound to light via microphone; master/slave function
Fixtures available for:	LED PC-Control 512
Maximum connection:	4 tubes
Display type:	3 digit 7-segment LED display
Output:	24 V DC;
Dimensions:	Width: 24 cm Depth: 29 cm Height: 6 cm
Weight:	2.05 kg

Scope of delivery:

- 1 x device
- 1 x user manual
- 1 x power cord