

OMNITRONIC PM-211P DJ Mixer with Player

2-channel DJ mixer with integrated MP3 player

Art. No.: 10006873

GTIN: 4026397467147



Features:

- Pre-fader listening (CUE) to the input channels via adjustable headphones output, with cue mix control
- Additional recording output
- 5-digit stereo LED level meter, switchable between master and PFL signal
- 2 input channels with gain control, 2-way equalizer and phono/line switching
- Desktop console housing

Logistic

EAN / GTIN: 4026397467147

Weight: 1,40 kg

Length: 0.30 m

Width: 0.20 m

Height: 0.10 m

Technical specifications:

Power supply:	230 V AC, 50 Hz 12V
Power consumption:	3.00 W
Protection class:	Protection class III
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>75 dB
THD:	<0.07 % at 1 kHz
Audio player:	USB
Control elements:	Crossfader, cue mix function, talkover

Status LED:	Channel level meter, master level meter, channel source, talkover
Connections:	Input: line via 2 x stereo RCA Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version Input: audio player via 1 x USB A (F) mounting version Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 2 x stereo with line-phono switch via RCA, channel control via fader, tone control EQ, gain control Input channel: 1 x stereo via audio player, channel control via rotary dial, talkover switch Microphone channel: 1 x mono via jack, channel control via rotary dial, cue mix function Master output: 1 x stereo via RCA, channel control via rotary dial Headphones output: 1 x stereo via jack, channel control via rotary dial
Music format:	MP3, WAV
Available storage media:	USB devices max. 32GB (FAT 32)
USB port:	Type A
Housing design:	Desktop console housing
Dimensions:	Width: 17 cm Depth: 14 cm Height: 6.5 cm
Weight:	1.15 kg

Scope of delivery:

1 x device
 1 x user manual
 1 x external mains adapter