

OMNITRONIC EM-280 Entertainment Mixer

8-channel stereo mixer with 2 adjustable zone outputs, 19"

Art. No.: 10007097

GTIN: 4026397714340



Features:

- 1 additional XLR microphone input in channel 1
- Nominal input level switchable between +4dBu and -10 dBV
- Signal and overload indicators in each channel
- 4-digit stereo level meter for each bus output
- (19") 48.3 cm rack installation 1 U
- For application areas such as: Installation; restaurants, bars and hotels; clubs/dancing school

Logistic

EAN / GTIN: 4026397714340

Weight: 3,65 kg

Length: 0.50 m

Width: 0.33 m

Heigh: 0.11 m

Technical specifications:

Power supply:	115/230 V AC, 50/60 Hz
Power consumption:	15 W
Protection class:	Protection class I
Power connection:	Power supply cord with safety plug (provided)
Fuse:	5 x 20 mm, T 1 A fuse replaceable
Frequency range:	20 - 20000 Hz
S/N ratio:	>92 dB line >65 dB microphone
THD:	Line <0.9 % at 1 kHz
Gain:	Mic/line 18 dB
Housing color:	Black

Control elements:	Groundlift selector
Status LED:	Power, master level meter, signal, clip
Connections:	Input: line via 8 x 6.3-mm-jack (bal.) Input: microphone via 1 x 3-pin XLR Output: master via 2 x 6.3-mm-jack (bal.) Output: AUX via 1 x 6.3-mm-jack (bal.) Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version Output: headphones via 1 x 3.5 mm jack (stereo) mounting version
Channels:	Input channel: 1 x mono + stereo with mic-line switch via XLR or jack, channel control via rotary dial, pre-post switch, gain control Input channel: 7 x stereo via jack, channel control via rotary dial, pre-post switch Master bus input: 2 x stereo via jack, routing master bus switch Master output: 2 x mono + stereo via XLR or RCA, channel control via rotary dial, stereo/mono switch Master bus output: 1 x stereo via jack Headphones output: 1 x stereo via jack, channel control via rotary dial, routing master bus switch
Housing design:	(19") 48.3 cm rack installation 1 U
Dimensions:	Width: 48.3 cm Depth: 28.0 cm Height: 4.4 cm
Weight:	3.06 kg

Scope of delivery:

1 x mixer
 1 x user manual
 1 x power cord
 1 x RCA cable