

OMNITRONIC CS-406 Powered mixer

Power mixer with 6 channels

Art. No.: 10050025

GTIN: 4026397183276



The article is no longer in our assortment.

Features:

- Low-noise 6-channel mic/line mixer and amplifier with 2 x 200 W/4 ohms output power
- Adjustable digital reverb
- 6 mono input channels (XLR and 6.3 mm jack) with gain control, 2-band EQ, pan and effect control
- Insert or direct out (6.3 mm jack) per input channel
- Aux send per channel for controlling external effectors
- Adjustable effect way for controlling external effect units (aux send/return)
- Tape input and output, switchable (stereo RCA)
- Adjustable headphones output (6.3 mm jack)
- +48V phantom power, can be switched centrally
- 2 x 7-band graphic equalizer for fine-tuned sound
- Precise 5-fold stereo LED meter
- 2 Speaker outputs

Logistic

EAN / GTIN: 4026397183276

Weight: 10,75 kg

Length: 0.36 m

Width: 0.35 m

Height: 0.52 m

Technical specifications:

Power supply: 115/230 V AC, 50/60 Hz

Power consumption: 800.00 W

Output power: Max. 400 W

Dimensions: Width: 44 cm
Depth: 26 cm
Height: 27.5 cm

Weight:	9.15 kg
Inputs:	
6 x mono	XLR or balanced 6.3 mm jacks
1 x Aux Return:	balanced 6.3 mm jack
1 x Tape In	stereo RCA
Outputs:	
1 x Main Out:	Speaker sockets
1 x Headphones	balanced 6.3 mm jack
1 x Aux Send:	balanced 6.3 mm jack
1 x Tape Out	stereo RCA
Frequency range:	
Microphone:	10-60000 Hz, ± 3 dB
Mono:	10-60000 Hz, ± 3 dB
Stereo:	10-55000 Hz, ± 3 dB
Distortion:	0.01 %
S/N ratio:	112 dB
Tone control/channel:	
Treble:	± 15 dB at 12 kHz
Middle:	± 15 dB at 2.5 kHz
Bass:	± 15 dB at 80 Hz
Power output sine:	
Stereo 4 ohms	2 x 200 W
Dimensions (W x D x H):	440 x 260 x 275 mm

Scope of delivery: