

OMNITRONIC CS-612 Powered mixer

Universal powered stage mixer

Art. No.: 10050125

GTIN: 4026397183290



The article is no longer in our assortment.

Features:

- Low-noise 12-channel mic/line mixer and amplifier with 2 x 300 W/4 ohms output power
- Digital reverb adjustable in 9 steps
- 8 mono input channels (XLR and 6.3 mm jack) with gain control, 3-band EQ, pan and effect control
- Insert or direct out (6.3 mm jack) per mono channel
- 2 stereo input channels (6.3 mm jack)
- Aux send per channel for controlling external effectors
- Adjustable effect way for controlling external effect units (aux send/return)
- Tape input and output, switchable (stereo RCA)
- Adjustable headphones output (6.3 mm jack)
- Stereo master output (6.3 mm jack)
- +48V phantom power, can be switched centrally
- 2 x 7-band graphic equalizer for fine-tuned sound
- Precise 5-fold stereo LED meter
- 2 Speaker outputs

Logistic

EAN / GTIN: 4026397183290

Weight: 17,00 kg

Length: 0.42 m

Width: 0.41 m

Height: 0.64 m

Technical specifications:

Power supply: 115/230 V AC, 50/60 Hz

Power consumption: 1000.00 W

Output power: Max. 600 W

Dimensions: Width: 52.5 cm
Depth: 30.5 cm

	Height: 32 cm
Weight:	14.50 kg
Inputs:	
8 mono	XLR or balanced 6.3 mm jacks
8 inserts	balanced 6.3 mm jacks
2 stereo	balanced 6.3 mm jacks
2 aux return	balanced 6.3 mm jacks
1 tape	RCA
Outputs:	
2 master	Speaker sockets, balanced 6.3 mm jacks
1 headphones	balanced 6.3 mm jack
2 aux send	balanced 6.3 mm jacks
8 insert	balanced 6.3 mm jacks
1 tape	RCA
Frequency range:	
Microphone:	10-60000 Hz, ± 3 dB
Mono:	10-60000 Hz, ± 3 dB
Stereo:	10-55000 Hz, ± 3 dB
Distortion:	0.01 %
S/N ratio:	112 dB
Tone control/channel:	
Treble:	± 15 dB at 12 kHz
Middle:	± 15 dB at 2.5 kHz
Bass:	± 15 dB at 80 Hz
Power output sine:	
Stereo 4 ohms	2 x 300 W
Dimensions (W x D x H):	525 x 305 x 320 mm

Scope of delivery: