

OMNITRONIC LH-042 Line/Phono Converter

Passive stereo line/phono converter

Art. No.: 10355042

GTIN: 4026397341218



Description:

The LH-042 converts a line signal to a phono signal. What this is good for? Just imagine the following situation. Your working as a DJ and you have recently bought a new line source (a CD player, MP3 player or the like). Now you would like to connect it to your mixer, but the line inputs are already used. What to do? At this point it's time for our LH-042. Just plug it into a phono input and connect your additional line source to the converter: you've got one more line slot for your mixer.

Logistic

EAN / GTIN: 4026397341218

Weight: 0,40 kg

Length: 0.23 m

Width: 0.14 m

Height: 0.08 m

Features:

- Converts a line signal to a phono signal
- Connect your line level sources, such as CD, MP3, DVD, or PC, to the magnetic phono input of a mixer, amplifier or recording unit
- Ground terminal for avoiding hum
- No power supply via power unit or battery necessary
- For application areas such as: Installation; mobile use; mobile djs / entertainer

Technical specifications:

Frequency range:	10 - 20000 Hz
S/N ratio:	>100 dB
Impedance:	Input: 10 kOhm Output: 470 Ohm
Gain:	-46 dB

Connections:	Input: line via 1 x stereo RCA
	Output: phono via 1 x stereo RCA
Material:	Metal
Color:	Silver
Dimensions:	Width: 9.8 cm
	Depth: 9.2 cm
	Height: 4 cm
Weight:	0.22 kg

Scope of delivery:

- 1 x device
- 4 x foot
- 1 x user manual