

OMNITRONIC Set PM-222 + 2x DD-2520

Set with 2-channel DJ mixer and two turntables

Art. No.: 20000396

GTIN:



Features:

- 2 input channels with gain control, 2-way equalizer and phono/line switching
 - DJ microphone input with separate level control
 - Pre-fader listening (CUE) to the input channels via adjustable headphones output, with cue mix control
 - Replaceable crossfader for crossfading between both channels
 - 6-digit stereo LED level meter and master level control
 - Outputs: master and record (stereo RCA)
 - Desktop console housing
 - For application areas such as: Clubs/dancing school; mobile djs / entertainer; installation
 - <p>OMNITRONIC DD-2520 USB Turntable bk
- Direct-drive DJ turntable with switchable phono/line output**
- Built-in USB port and additional phono preamplifier, for a high-quality and convenient digitization of analog vinyl records
 - Driver installation not required, unit is identified automatically
 - Sampling rates of 44.1 kHz and 48 kHz in stereo, resolution: 16 bits
 - Incl. software for recording and editing
 - Precision direct drive
 - Delivery includes pick-up system
 - 2 speeds, pitch control $\pm 10\%$
 - Large start/stop button
 - Strobe lamp for exact speed adjustment
 - Target lamp
 - Delivery includes removable dustcover
 - Adjustable anti-skating
 - Shock-absorbing feet
 - Switchable output phono/line

Logistic

- USB 1.1 support
- Suitable for Windows XP, Vista, 7 and Mac OS X
- Pitch range: $\pm 10\%$
- The device can be connected via USB to the PC

Technical specifications:

Weight:	24.50 kg
---------	----------

OMNITRONIC PM-222 2-channel DJ Mixer

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	30.00 W
Protection class:	Protection class II
Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>70 dB
THD:	<0.025 % at 1 kHz
Impedance:	Input: microphone 47 kOhm Input: line 47 kOhm Input: phono 47 kOhm
Gain:	Input: variable
Control elements:	Power switch, source selector, crossfader
Status LED:	Master level meter, power
Connections:	Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version Input: line via 4 x stereo RCA Input: phono via 2 x stereo RCA Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 2 x stereo with line-line-phono switch via RCA, channel control via fader, 2-band tone control EQ, gain control Microphone channel: 1 x mono via jack, channel control via rotary dial, cue mix function Master output: 1 x stereo via RCA, channel control via rotary dial Headphones output: 1 x stereo via jack, channel control via rotary dial
Max. level:	Output: master +19 dBu
Housing design:	Desktop console housing
Dimensions:	Width: 19 cm Depth: 26 cm Height: 13.7 cm
Weight:	2.00 kg

OMNITRONIC DD-2520 USB Turntable bk

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	12.00 W
Power connection:	Fixed power supply cord with Euro plug
Frequency range:	20 - 20000 Hz
Drive type:	Direct drive Brushless DC motor
Drive:	Initial torque: 1 kg/cm Start time: 1 sec. Stop time: 1 sec. Speed change time: <1s 1kHz 5cm/sec
Wow and flutter:	<0.15 % WRMS
Rumble:	55 dB DIN B
Speed:	33 RPM; 45 RPM
Tone arm:	S-shape with Cardan"s suspension Length: 230 Overhang: 16 mm Stylus pressure: 0-4 g, adjustable
Output level:	Phono 1.5-3.6 mV/ 1 kHz 5 cm/sec Line 90-216 mV/ 1 kHz 5 cm/sec
Connections:	Output: line/phono via stereo RCA Output: USB B (F) mounting version
Pitch range:	±10%
USB port:	1 x USB 1.1, type B
Color:	Black
PC connect:	Via USB
Dimensions:	Width: 45 cm Depth: 35 cm Height: 15.5 cm
Weight:	11.25 kg
Dimensions:	Diameter: Ø 33 cm

Scope of delivery:**1 x OMNITRONIC PM-222 2-channel DJ Mixer**

1 x user manual
1 x power cord
1 x mixer

2 x OMNITRONIC DD-2520 USB Turntable bk

1 x system
1 x turntable platter