

EUROLITE DMX Move Controller 512

Controller with color & motion effects (28 devices, 18 control channels each)

Art. No.: 70064515

GTIN: 4026397511352



Features:

- DMX controller for DMX light effect units such as moving heads, scanners and LED spot lights with RGBW color mixture
- 512 DMX channels can be assigned and inverted as desired to 32 control channels (softpatch)
- For 28 fixtures with 18 control channels each
- USB port for storing program data
- Quick programming thanks to 9 integrated movement patterns and 7 color effects (PAN/TILT position, fade time and running time adjustable)
- Manual, time-controlled or sound-controlled chase running mode
- 2 DMX fixture levels can be controlled, each with up to 18 channels
- 16 DMX channel faders
- 2 jog wheels for pan/tilt
- Blackout function
- Can transmit up to 512 DMX channels
- (19") 48.3 cm rack installation 3 U
- Programmable 32 scenes/chases each with 600 cues
- Control via DMX; RDM
- Monochrome LCD display
- Firmware can be updated
- Desktop console housing
- For application areas such as: Clubs/dancing school; stage; mobile djs / entertainer
- Silent operation

Logistic

EAN / GTIN: 4026397511352

Weight: 2,78 kg

Length: 0.58 m

Width: 0.18 m

Height: 0.14 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	2.70 W
Protection class:	Protection class III
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord with AC adapter (provided)
Programs:	Programmable 32 scenes/chases each with 600 cues
DMX channels:	Output 512
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; RDM
Housing color:	Black
Display type:	Monochrome LCD display
Available storage media:	USB devices (FAT 32)
USB port:	Type A
PC connect:	, firmware can be updated
Housing design:	(19") 48.3 cm rack installation 3 U Desktop console housing
Dimensions:	Width: 48.3 cm Depth: 13 cm Height: 8.9 cm
Weight:	2.39 kg
Noise classification:	Class 0 (no noise at all)

Scope of delivery:

1 x controller
1 x user manual
1 x external mains adapter