



Features:

- Auto-switching transceiver
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Can receive and process up to 512 DMX channels
- Can transmit up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Logistic

EAN / GTIN: 4026397532159
Weight: 0,36 kg
Length: 0.14 m
Width: 0.12 m
Heigh: 0.06 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz 5V DC 500 mA
Power connection:	Mains input via USB C (W) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Input 512 Output 512
DMX input:	1 x 3-pin XLR (M) mounting version

DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
RF power output:	19 dBm
Modulation:	GFSK
Color:	Black
Dimensions:	Width: 21.2 cm
	Depth: 10 cm
	Height: 7.5 cm
Weight:	0.29 kg

Scope of delivery:

- 1 x device
- 1 x user manual
- 1 x external mains adapter
- 1 x USB cable
- 1 x antenna
- 1 x declaration of conformity