

## OMNITRONIC PM-202FX 2-Channel DJ Mixer with Filter, FX and Bluetooth

Art. No.: 10006865

DJ mixer with Bluetooth connectivity, bipolar filter and 6 sound effects

GTIN: 4026397731088



**List price: 236.81 €**

incl. 19% VAT.

### Features:

- Bluetooth signal routable to channel 1 and 2
- DJ microphone channel with level control and 2-band equalizer
- DJ filter LPF/HPF bipolar per channel
- Crossfader with adjustable curve and reverse function
- Master channel with level control and stereo LED level meter
- 4 line and 2 phono inputs via RCA jacks
- Additional recording output
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Control via Bluetooth
- Bluetooth: operating range up to 15m
- Desktop console housing
- For application areas such as: Party room; mobile use; mobile djs / entertainer

### Logistic

EAN / GTIN: 4026397731088

Weight: 2,75 kg

Length: 0.36 m

Width: 0.25 m

Height: 0.15 m

### Technical specifications:

|                    |                                                                                                |
|--------------------|------------------------------------------------------------------------------------------------|
| Power supply:      | 100-240 V AC, 50/60 Hz                                                                         |
| Power consumption: | Max. 8 W                                                                                       |
| Protection class:  | Protection class II                                                                            |
| Power connection:  | Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided) |
| Frequency range:   | 20 - 20000 Hz                                                                                  |

|                        |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| S/N ratio:             | >80 dB                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| THD:                   | <0.1 % at 1 kHz                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
| DJ filter:             | Per channel: LPF/HPF bipolar,                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| DJ-FX:                 | Master: CHORUS, REVERB, DELAY, FLANGER<br>Master: WHA, PHASE,                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| Control:               | Bluetooth                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| Bluetooth device name: | PM-202FX                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| Range:                 | Bluetooth: range up to 15m                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Crosstalk:             | >60 dB                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| Control elements:      | Crossfader, Crossfade curve control, crossfade reverse switch, FX Parameter control, power switch                                                                                                                                                                                                                                                                                                                                                                                                                          |
| Status LED:            | Power, master level meter                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| Connections:           | Input: line/phono via 2 x stereo RCA<br>Input: line via 2 x stereo RCA<br>Input: microphone via 1 x 3-pin XLR (F) mounting version<br>Input: antenna via 1 x SMA (F) mounting version<br>Input: Earthing connection via 2 x screw terminal<br>Output: master via 2 x 3-pin XLR (M) mounting version<br>Output: master via 1 x stereo RCA<br>Output: rec. via 1 x stereo RCA<br>Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version<br>Output: headphones via 1 x 3.5 mm jack (stereo) mounting version |
| Channels:              | Input channel: 2 x stereo with Line-Line/Phono-Bluetooth switch via RCA, channel control via 60mm fader, 2-band tone control EQ, gain control, CUE switch<br><br>Microphone channel: 1 x mono via XLR, channel control via rotary dial, 2-band tone control EQ<br><br>Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol<br><br>Headphones output: stereo via jack, channel control via rotary dial, cue mix function<br><br>Rec. output: stereo via RCA                            |
| Material:              | Metal                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Color:                 | Black                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Housing design:        | Desktop console housing                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| Dimensions:            | Length: 30.5 cm<br>Width: 19.0 cm<br>Height: 11.0 cm                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| Weight:                | 2.18 kg                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |
| Cable length:          | 2.10 m detachable                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |

## Scope of delivery:

1 x mixer  
 1 x power cord  
 1 x antenna  
 1 x RCA cable  
 1 x user manual  
 1 x declaration of conformity