

OMNITRONIC PM-422P 4-channel DJ Mixer with Bluetooth & USB Player

4-channel DJ mixer with Bluetooth and MP3 player

Art. No.: 10006878

GTIN: 4026397653410



Features:

- 4 input channels with gain control, LED level meter, 3-band equalizer, cue button and channel fader
 - DJ microphone channel with level control, 2-band equalizer, on/off and talkover switch
 - Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
 - Crossfader with assignment switches and adjustable curve
 - Master channel with level and balance control
 - 10-digit stereo LED level meter
 - Adjustable monitor output
 - 10 line and 2 phono inputs via RCA jacks
 - Balanced XLR and RCA outputs
 - Record output, independent of the master
 - Desktop console housing
 - For application areas such as: Party room; mobile djs / entertainer; mobile use
- audio player**
- Control via Bluetooth
 - LCD display

Logistic

EAN / GTIN: 4026397653410

Weight: 4,17 kg

Length: 0.37 m

Width: 0.29 m

Height: 0.13 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption: 6.5 W

Protection class: Protection class II

Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>65 dB
THD:	<0.1 % at 1 kHz Microphone <1.0 % at 1 kHz
Housing color:	Black
Control elements:	Audio player, talkover, crossfader selector switch, crossfader, crossfade curve switch
Status LED:	Channel level meter, master level meter, CUE, ON AIR, power
Connections:	Input: line via 6 x stereo RCA Input: line/phono via 2 x stereo RCA Input: microphone via 1 x 6.3 mm jack socket (mono) mounting version Input: audio player via 1 x USB A (F) mounting version Output: master via 1 x stereo RCA Output: master via 2 x 3-pin XLR Output: rec. via 1 x stereo RCA Output: booth via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version
Channels:	Input channel: 1 x stereo with line-line-player switch via RCA or player, channel control via fader, 3-band tone control EQ, gain control, CUE switch Input channel: 1 x stereo with line-line switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch Input channel: 2 x stereo with line-line/phono switch via RCA, channel control via fader, 3-band tone control EQ, gain control, CUE switch Microphone channel: 1 x mono via jack, channel control via rotary dial, 2-band tone control EQ, talkover switch, ON AIR switch Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol Booth output: 1 x stereo via RCA, channel control via rotary dial, cue mix function Headphones output: 1 x stereo via jack, channel control via rotary dial
Housing design:	Desktop console housing
Dimensions:	Length: 35 cm Width: 26.6 cm Height: 10.5 cm
Weight:	3.46 kg
Control:	Bluetooth
Bluetooth:	Version: 4.2 + EDR Profiles: A2DP, AVRCP
Bluetooth device name:	PM-422P
Audio player:	USB + Bluetooth
Carrier frequency:	2.4 GHz
Display type:	LCD display

Display reading:	Singer , song title , play time remaining , play time elapsed; ID3-Tags
Music format:	MP3, WMA; WAV
Available storage media:	USB devices max. 32GB (FAT 32)
USB port:	Type A

Scope of delivery:

- 1 x mixer
- 1 x user manual
- 1 x power cord
- 1 x RCA cable
- 1 x declaration of conformity