

OMNITRONIC CFL-1642 Live Mixer

16-channel live mixer

Art. No.: 10060325

GTIN: 4026397230871



Description:

Something for everybody. The smallest unit of this CFL live mixer series disposes of 12, the biggest unit disposes of 32 mono inputs. Normally, live mixers have faders from 70 - 80 mm. The CFL series has remarkably long faders that easily reach 100 mm. Although it is very low-priced, the series is highly resistant and by offering four subgroups and four Aux-Sends it is really well equipped. In total: powerful but not pricy.

Logistic

EAN / GTIN: 4026397230871

Weight: 18,65 kg

Length: 0.87 m

Width: 0.25 m

Height: 0.66 m

Features:

- 16 mono inputs with XLR sockets and balanced line inputs
- +48V phantom power per channel
- 2 stereo inputs via balanced jacks
- 2 stereo effect returns
- Insert for every mono channel
- High pass filter and 3-band EQ with semi-parametric mids for all mono inputs
- 4 groups for levelling complete signal groups (e.g. drums)
- Mutes for every channel
- 4 aux send (2 pre, 2 post) per channel for controlling the effects and for monitoring
- Separate master, group, monitor outputs
- 100 mm faders
- Precise 12-digit LED meter in subgroups and stereo master

Technical specifications:

Power supply: 115/230 V AC, 50/60 Hz

Power consumption:	50.00 W
Dimensions:	Width: 78 cm Depth: 53 cm Height: 16 cm
Weight:	15.90 kg
Inputs:	
16 mono	XLR or balanced 6.3 mm jacks
16 inserts	6.3 mm jacks
2 stereo	6.3 mm jacks
4 Aux-Return	balanced 6.3 mm jacks
Outputs:	
2 Main Out:	XLR or balanced 6.3 mm jacks
1 Monitor	balanced 6.3 mm jack
4 Aux Send:	balanced 6.3 mm jack
Rec Out	RCA
Frequency range:	10-60000 Hz, ±3 dB
Dimensions (W x D x H):	780 x 530 x 160 mm

Scope of delivery: