

OMNITRONIC GEQ-231 FD Equalizer 2x31-band

2 x 31-band equalizer with feedback display

Art. No.: 10355545

GTIN: 4026397233247



The article is no longer in our assortment.

Features:

- 2-channel version, 2 x 31 frequency controls with 2/3 octave steps
- Long sliding frequency controls with center click
- Adjustable feedback threshold
- EQ gain switchable ± 6 dB to ± 15 dB
- Hi Cut (4-30 kHz) and Low Cut (10-300 Hz), switchable
- Separate level control per channel
- Bypass switch allows instant comparison of the original sound with the equalized sound
- 7-fold LED level meter with clip indicator
- Inputs and outputs via 6.3 mm jack sockets (1/4"), XLR sockets and screw terminals
- Groundlift switch
- Rack installation, 3 U

Logistic

EAN / GTIN: 4026397233247

Weight: 5,70 kg

Length: 0.54 m

Width: 0.25 m

Height: 0.17 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	10.00 W
Dimensions:	Width: 48.3 cm Depth: 17.5 cm Height: 13.35 cm
Weight:	5 kg
Input impedance:	10/20 kohms (unb./bal.)
Output impedance:	300/150 kohms (unb./bal.)

In/Out connectors:	XLR, jack, screw terminals
S/N ratio:	>95 dB
Crosstalk:	>90 dB
Distortion:	<0.01 %
Frequency range:	20-20000 Hz, ±0.5 dB
Output level:	- ~ to +6 dB
Control range:	±6 dB or ±12 dB
Frequencies:	2 x 20/25/31.5/40/50/63/80/100/125/160/200/250/ 315/400/500/ 630/800 Hz, 1/1.25/1.6/2/2.5/3.15/4/5/6.3/8/10/12.5/16/20 kHz
Hi Cut:	4-30 kHz
Low Cut:	30-300 Hz
Dimensions (W x D x H):	483 x 175 x 133 mm

Scope of delivery: