

EUROLITE Set QuickDMX 1x transmitter + 4x Receiver

Wireless DMX transmitter including 4x compact wireless DMX receiver

Art. No.: 20000646

GTIN: 4026397009774



Features:

- User-friendly 3-pin XLR adapter (male) with swivel antenna
 - Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
 - Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
 - 1 to 512 QuickDMX receivers can be controlled by each transmitter
 - LED indication for functions
 - Transceiver, to be used as transmitter or receiver
 - Can transmit up to 512 DMX channels
 - Control via QuickDMX; DMX; plug and play
 - Operating range up to 400m
 - Up to 6 transmitters can be operated in parallel without interference
 - <p>EUROLITE QuickDMX Wireless Receiver
- Compact wireless DMX receiver 2.4 GHz**
- User-friendly 3-pin XLR adapter (female) with swivel antenna
 - Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
 - Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
 - 1 to 512 QuickDMX receivers can be controlled by each transmitter
 - LED indication for functions
 - Transceiver, to be used as transmitter or receiver
 - Can receive and process up to 512 DMX channels
 - Control via QuickDMX; plug and play
 - Operating range up to 400m
 - Up to 6 transmitters can be operated in parallel without interference

Logistic

EAN / GTIN: 4026397009774

Weight: 1,20 kg

Length: 0.30 m

Width: 0.22 m

Heigh: 0.21 m

Technical specifications:

Weight:	0.79 kg
---------	---------

EUROLITE QuickDMX Wireless Transmitter

Power supply:	100-240 V AC, 50/60 Hz 5V DC 1000 mA
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)
Control:	QuickDMX; DMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
RF power output:	19 dBm
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21.2 cm Diameter: Ø 1.8 cm
Weight:	0.15 kg

EUROLITE QuickDMX Wireless Receiver

Power supply:	100-240 V AC, 50/60 Hz 5V DC 1000 mA
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Input 512
DMX output:	3-pin XLR (F)
Control:	QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
RF power output:	19 dBm
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21.2 cm Diameter: Ø 1.8 cm
Weight:	0.16 kg

Scope of delivery:

1 x EUROLITE QuickDMX Wireless Transmitter

1 x device
1 x user manual
1 x declaration of conformity
1 x external mains adapter
1 x USB cable

4 x EUROLITE QuickDMX Wireless Receiver

1 x device
1 x user manual
1 x declaration of conformity
1 x external mains adapter
1 x USB cable