



List price: 570.01 €

incl. 19% VAT.

Features:

EUROLITE QuickDMX Wireless Transmitter

Compact wireless DMX transmitter 2.4 GHz

- User-friendly 3-pin XLR adapter (male) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can transmit up to 512 DMX channels
- Control via QuickDMX; DMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

EUROLITE AKKU QuickDMX Wireless Receiver

Battery-powered wireless DMX receiver 2.4 GHz

- Compact 3-pin XLR adapter (female) with built-in antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations

Logistic

EAN / GTIN: 4026397697575

Weight: 2,00 kg

Length: 0.00 m

Width: 0.00 m

Height: 0.00 m

- 32-bit ARM processor for delay-free transmission
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Group mode
- Multicolored LED indicator
- Cordless, flexible and versatile
- Battery operation up to 20h
- Control via QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Technical specifications:

Weight:	0.96 kg
---------	---------

EUROLITE QuickDMX Wireless Transmitter

Power supply:	100-240 V AC, 50/60 Hz 5V DC 1000 mA
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Output 512
DMX input:	1 x 3-pin XLR (M)
Control:	QuickDMX; DMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
RF power output:	19 dBm
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21.2 cm Diameter: Ø 1.8 cm
Weight:	0.15 kg

EUROLITE AKKU QuickDMX Wireless Receiver

Power supply:	5V DC
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
Battery pack type:	1 x lithium ion 3.7 V, 450 mAh, 1.665 Wh
Battery pack:	Battery operation up to 20h
DMX output:	3-pin XLR (F)
Control:	QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz

Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 9.50 cm Diameter: Ø 1.8 cm
Weight:	0.14 kg

Scope of delivery:

1 x EUROLITE QuickDMX Wireless Transmitter

1 x device
1 x user manual
1 x declaration of conformity
1 x external mains adapter
1 x USB cable

6 x EUROLITE AKKU QuickDMX Wireless Receiver

1 x device
1 x user manual
1 x declaration of conformity
1 x external mains adapter
1 x USB cable