

FUTURELIGHT WDR USB Wireless DMX Receiver  
Wireless miniature DMX receiver with LumenRadio technology, 2.4 GHz

Art. No.: 51834034  
GTIN: 4026397702453



Features:

- User-friendly USB plug with swivel antenna
- Can be used with all EUROLITE/FUTURELIGHT fixtures with WirelessDMX USB port
- Adaptive frequency hopping ensures interference-free operation in the 2.4 GHz band
- LED indicator for monitoring the operating status
- Can receive and process up to 512 DMX channels
- Control via W-DMX by wireless solution; CRMX by LumenRadio; plug and play
- Operating range up to 600m with line-of-sight

Logistic

EAN / GTIN: 4026397702453  
Weight: 0,06 kg  
Length: 0.09 m  
Width: 0.06 m  
Heigth: 0.02 m

Technical specifications:

|                    |                                                               |
|--------------------|---------------------------------------------------------------|
| Power connection:  | Mains input via USB A (M) connectable version                 |
| DMX channels:      | Input 512                                                     |
| DMX output:        | USB, type A                                                   |
| Phantom power:     | 5 V DC                                                        |
| Control:           | W-DMX by wireless solution; CRMX by LumenRadio; plug and play |
| Range:             | Range up to 600m with line-of-sight                           |
| Carrier frequency: | 2.4 GHz                                                       |
| Modulation:        | AFHSS                                                         |
| Color:             | Black                                                         |

|             |                |
|-------------|----------------|
| Dimensions: | Length: 8.6 cm |
|             | Width: 4.1 cm  |
|             | Height: 1.1 cm |
| Weight:     | 0.02 kg        |

**Scope of delivery:**

---

1 x USB stick  
1 x user manual  
1 x declaration of conformity