

FUTURELIGHT WDS-CRMX TX Wireless DMX Transceiver

Wireless DMX system (2.4 GHz) - compact transceiver with CRMX unit

Art. No.: 51834037

GTIN: 4026397726718



List price: 296.31 €

incl. 19% VAT.

Features:

- Transceiver, to be used as transmitter or receiver
- Adaptive frequency hopping ensures interference-free operation in the 2.4 GHz band
- Can receive and process up to 512 DMX channels
- Can transmit up to 512 DMX channels
- Multicolored LED indicator
- Control via CRMX by LumenRadio; W-DMX by wireless solution
- Operating range up to 600m with line-of-sight
- Up to 10 transmitters can be operated in parallel without interference
- With a KENSINGTON LOCK theft protection

Logistic

EAN / GTIN: 4026397726718
Weight: 0,89 kg
Length: 0.25 m
Width: 0.18 m
Heigh: 0.08 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	2 W
Power connection:	Mains input via P-Con (blue), mounting version power supply cord with safety plug
Fuse:	T 1 A fuse fix in power supply
DMX channels:	Input 512 Output 512
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version

Control:	CRMX by LumenRadio; W-DMX by wireless solution
Range:	Range up to 600m with line-of-sight
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 10 transmitter
Antenna gain:	3 dBi
Modulation:	GFSK
Attachment system:	M10 thread
Status LED:	DMX, level meter
Color:	Black
Theft protection:	KENSINGTON LOCK
Dimensions:	Length: 14.1 cm Width: 9.8 cm Height: 5.6 cm
Weight:	0.70 kg

Scope of delivery:

1 x device
 1 x user manual
 1 x power cord
 1 x declaration of conformity