

FUTURELIGHT DMD-512 DMX Monitor Driver
Convenient DMX monitor driver

Art. No.: 51834650
GTIN: 4026397336047



The article is no longer in our assortment.

Features:

- For equipping simple DMX controllers with monitor, mouse, keyboard and PC connection
- 1024 control channels
- 3 working modes: DMX receiver (2 x 512 channels), DMX converter (1 x 512 channels), DMX controller (1024 channels)
- Comfortable adjustment of different parameters
- Change channel values
- Group DMX-channels
- DMX-channels can be inverted
- Include virtual Master Fader
- Built-in clock
- Recommended monitor resolution 1280 x 1024 pixels, 60 Hz
- Can receive and process up to 1024 DMX channels
- Can transmit up to 1024 DMX channels
- Control via DMX
- Interface
- Made in Europe

Logistic

EAN / GTIN: 4026397336047
Weight: 1,17 kg
Length: 0.40 m
Width: 0.11 m
Heigh: 0.09 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	6.00 W
Protection class:	Protection class III
DMX channels:	Input 1024

	Output 1024
DMX input:	2 x 3-pin XLR (M) mounting version
DMX output:	2 x 3-pin XLR (F) mounting version
Control:	DMX
Housing color:	Black
Color:	Black
Housing design:	Interface
Dimensions:	Width: 31.5 cm
	Depth: 7.5 cm
	Height: 6.8 cm
Weight:	1.01 kg

Scope of delivery: