

EUROLITE freeDMX Wi-Fi Interface

USB DMX interface with Wi-Fi module - for EUROLITE Light'J app

Art. No.: 51860125

GTIN: 4026397506587



Features:

- DMX interface with integrated Wi-Fi module for wireless control of DMX devices
- freeDMX allows control of DMX devices through smartphones or tablet PCs more flexible than ever - right now true for Eurolite KLS and Hybrids
- For mobile iOS and Android devices
- Download matching apps from the App Store and Google Play
- Applicable as USB DMX interface for controlling DMX devices with a computer
- Supports various DMX software applications
- Fully supported by FreeStyler as of version 3.37 (freeware)
- Input or output of 512 DMX channels
- Windows XP, Vista, 7 and 8, Linux OLA-OpenDMX.net
- 3-pin Neutrik XLR connectors for DMX IN/DMX OUT
- USB 2.0 port
- Status LEDs for Wi-Fi, USB, DMX IN and DMX OUT
- Supports firmware updates
- Driver and firmware updater available for download at www.eurolite.de
- Powered via included PSU

Logistic

EAN / GTIN: 4026397506587

Weight: 0,26 kg

Length: 0.16 m

Width: 0.12 m

Height: 0.06 m

Technical specifications:

Dimensions:	Width: 9.8 cm
	Depth: 8.8 cm
	Height: 5.2 cm

Power supply:	5 V DC, 1.2 A
---------------	---------------

	via included PSU
Wi-Fi standard:	IEEE 802.11g/b/n
Frequency range:	2.4 GHz range (ISM), 11 channels
Übertragungstyp:	DDSS/OFDM
Data rate:	1-11 Mbps (802.11b), 6-54 Mbps (802.11g)
Antenna:	2 dBi
DMX512 output:	1 universe (512 channels)
DMX connectors:	3-pin XLR mounting socket, 3-pin XLR mounting plug, Neutrik
USB port:	USB 2.0, type B
Dimensions (w/o antenna):	L 98 x W 88 x H 52 mm
Weight:	350 g

Scope of delivery: