

EUROLITE DTB-405 4-channel Dimmerbar 5A

Dimmer bar for chaser or DMX operation

Art. No.: 70064420

GTIN: 4026397108057



The article is no longer in our assortment.

Features:

- Makes the installation of your lighting system really easy
- Installed directly on the stand or crossbeam
- With 4 spot connections
- Outputs via 4 safety sockets
- Can be used either as a 4-channel chaser controller or a DMX dimmer pack
- 6 different operation modes
- 16 pre-programmed chaser patterns
- Chaser direction can be inverted
- Chaser speed controllable or sound-controlled
- Sound control via built-in microphone
- Remote control via optional footswitch
- Only for professional use
- **device**
- Cordless, flexible and versatile

Logistic

EAN / GTIN: 4026397108057

Weight: 6,00 kg

Length: 1.35 m

Width: 0.21 m

Height: 0.27 m

Bulky product

Technical specifications:

Power supply: 230 V AC, 50 Hz

Output current: Max. 5 A per channel

Dimensions: Width: 130 cm
Depth: 10 cm
Height: 10.5 cm

Weight: 5.05 kg

Battery pack type:	1 x nickel metal hydride 3.6 V,
Max. power output:	3680 W
Max. total current:	16 A
Max. output/channel:	1150 W
Max. current/channel:	5 A
Fuse:	F 6.3 A, 250 V
Maximum load per fixation point:	4 kg
Max. spaced braceload:	16 kg
Max. centered braceload:	25 kg
TV spigot:	D = 28 mm
Dimensions (L x W x H):	1300 x 100 x 105 mm

Scope of delivery:

1 x device