

EUROLITE AKKU QuickDMX Wireless Receiver

Battery-powered wireless DMX receiver 2.4 GHz

Art. No.: 70064699

GTIN: 4026397690149



List price: 83.18 €

incl. 19% VAT.

Features:

- Compact 3-pin XLR adapter (female) with built-in antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- 32-bit ARM processor for delay-free transmission
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Group mode
- Multicolored LED indicator
- Cordless, flexible and versatile
- Battery operation up to 20h
- Control via QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Logistic

EAN / GTIN: 4026397690149

Weight: 0,21 kg

Length: 0.14 m

Width: 0.12 m

Height: 0.06 m

Technical specifications:

Power supply:	5V DC
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
Battery pack type:	1 x lithium ion 3.7 V, 450 mAh, 1.665 Wh
Battery pack:	Battery operation up to 20h
DMX output:	3-pin XLR (F)

Control:	QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 9.50 cm
	Diameter: Ø 1.8 cm
Weight:	0.14 kg

Scope of delivery:

1 x device
1 x user manual
1 x declaration of conformity
1 x external mains adapter
1 x USB cable