

MP-180P PA Mixing Amplifier

PA mixing amplifier with audio player, IR remote control, 180 W RMS

Art. No.: 80709631

GTIN: 4026397503463



MP-180P PA Mixing Amplifier

PA mixing amplifier with audio player, IR remote control, 180 W RMS

Art. No.: 80709631

GTIN: 4026397503463

Features:

- SD card slot and USB port
- Folder navigation and repeat functions (1, All)
- 3 microphone inputs (6.3 mm jack, unbal.) with separate level controls
- Microphone input 3 with adjustable priority circuit
- 3 line inputs (stereo RCA) with separate level controls
- 1 line output (stereo RCA)
- Chime, switchable
- Treble and bass control for the output signal
- 7-digit LED level meter
- Master control for the output signal
- (19") 48.3 cm rack installation 2 U
- The device is cooled by cooling fan
- Control via IR remote control
- For application areas such as: Installation; restaurants, bars and hotels; sports centres/gyms