

MPVZ-180.6P PA Mixing Amplifier

6-zone-PA mixing amplifier with audio player and remote control, adjustable zones, 180 W RMS

Art. No.: 80709782

GTIN: 4026397503517



MPVZ-180.6P PA Mixing Amplifier

6-zone-PA mixing amplifier with audio player and remote control, adjustable zones, 180 W RMS

Art. No.: 80709782

GTIN: 4026397503517

Features:

- Comfortable control of PA speakers via 6-zone technology
- 6 PA zone outputs with separate 5-step level controls
- Output for low-impedance speakers (4-16 ohms)
- SD card slot and USB port
- Folder navigation and repeat functions (1, All)
- 2 rear microphone inputs (6.3 mm jack, unbal.)
- 1 front microphone input (combination XLR/6.3 mm jack, unbal.) with adjustable priority circuit
- All microphone inputs with separate level controls
- 3 line inputs (stereo RCA) with separate level controls
- 1 line output (stereo RCA)
- Chime, switchable
- Treble and bass control for the output signal
- 7-digit LED level meter
- Master control for the output signal
- (19") 48.3 cm rack installation 2 U
- Highly efficient air flow from front to rear
- The device is cooled by temperature-controlled fan