OMNITRONIC PA 6-zone mono vol contr 10W sil

6-way PA volume controller with 24 V emergency priority relays

Art. No.: 80711329

GTIN: 4026397262377









Features:

- 6 audio transformers for 100 V line technique
- Attenuation in 10 steps
- 6 built-in 24 V emergency priority relays
- Aluminum front panel
- Screw plug connection
- (19") 48.3 cm rack installation 2 U

Logistic

EAN / GTIN: 4026397262377
Weight: 3,60 kg
Length: 0.51 m
Width: 0.25 m
Heigth: 0.15 m

Technical specifications:

Priority relay:	24 V
Power:	Rated: 6x 10W RMS
Frequency range:	50 - 18000 Hz
Zone output:	6
Input & output:	Mono
Housing design:	(19") 48.3 cm rack installation 2 U
Dimensions:	Width: 48.3 cm Depth: 23 cm Height: 8.9 cm
Weight:	3.00 kg

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn
All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

Scope of delivery:

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn
All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.