

## OMNITRONIC ELA-T20 Transformer 20 W

100 V audio transformer

Art. No.: 80711403

GTIN: 4026397271348



**List price: 17.73 €**

incl. 19% VAT.

### Features:

- For amplifiers or speakers without built-in 100 V audio transformer
- Converts low-impedance signals into 100 V signals
- 5 power taps

### Logistic

EAN / GTIN: 4026397271348

Weight: 0,39 kg

Length: 0.08 m

Width: 0.04 m

Height: 0.04 m

### Technical specifications:

|                    |                                                                    |
|--------------------|--------------------------------------------------------------------|
| Power:             | Rated: 20W RMS                                                     |
| Frequency range:   | 40 - 17000 Hz                                                      |
| Impedance:         | Public address systems 100V; 4 ohms; 8 ohms; 16 ohms               |
| Power tapping:     | 2.5W; 5W; 10W; 15W; 20W RMS via no connector/cable only switchable |
| Borehole distance: | 6.3 cm                                                             |
| Dimensions:        | Width: 8.5 cm<br>Depth: 5.4 cm<br>Height: 5 cm                     |
| Weight:            | 0.38 kg                                                            |

## Scope of delivery:

---

1 x device  
1 x user manual