

OMNITRONIC ELA-T20 Transformer 20 W

100 V audio transformer

Art. No.: 80711403

GTIN: 4026397271348



Features:

- For amplifiers or speakers without built-in 100 V audio transformer
- Converts low-impedance signals into 100 V signals
- 5 power taps

Logistic

EAN / GTIN: 4026397271348

Weight: 0,39 kg

Length: 0.08 m

Width: 0.04 m

Heigth: 0.04 m

Technical specifications:

Power:	Rated: 20W RMS
Frequency range:	40 - 17000 Hz
Impedance:	Public address systems 100V; 4 ohms; 8 ohms; 16 ohms
Power tapping:	2.5W; 5W; 10W; 15W; 20W RMS via no connector/cable only switchable
Borehole distance:	6.3 cm
Dimensions:	Width: 8.5 cm Depth: 5.4 cm Height: 5 cm
Weight:	0.38 kg

Scope of delivery:

1 x device

1 x user manual