EUROLITE LVH-4 Video booster

Video line amplifier with equalizer

Art. No.: 81013204

GTIN: 4026397324815

Description:

The Video Booster amplifies your signal to keep the quality high even over long distances of up to 600 meters. Of course, it can also be used to amplify a naturally weak signal to reach the desired quality standard. All this comes in an extremely compact design.

Features:

- Equalizes and compensates for signal losses inherent in long cable runs (max. 600 m)
- 75 ohms input and outputs via BNC plugs
- Separate controls for amplification and equalization
- Ultra compact

Technical specifications:

Power supply:	12-24V DC 30 mA 12-24V AC 30 mA
S/N ratio:	>70 dB
Dimensions:	Width: 7.6 cm Depth: 4.1 cm Height: 3.1 cm
Weight:	0.07 kg
1 x video input:	1 Vpp/ 75 ohms, BNC

Logistic

EAN / GTIN: 4026397324815
Weight: 0,09 kg
Length: 0.09 m
Width: 0.04 m
Heigth: 0.05 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn
All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

1 x video output:	1 Vpp/ 75 ohms, BNC
Gain:	adjustable to +5 dB
Bandwidth:	10 MHz
Equalization adjustment:	0 dB to +4 dB/ 3.58 MHz
	0 dB to +7 dB/ 5 MHz

Scope of delivery:

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn
All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.